SOLUTION:

It is not hardware defective. Do not replace any hardware. Please follow below steps to install:

STEP1: Shutdown computer. Press NOVO button, then use " \downarrow " key to select [BIOS Setup] and hit the Enter key.

Novo Button Menu	
Normal Startup BIOS Setup	
Boot Menu System Recovery	

STEP2: If the BIOS version is lower than A7CN27WW, please update BIOs to 27 or above. BIOS can be found on support website, or, contact local support center if necessary.

Distantian & Manage	Lenovo G/0-30
BIOS Version	A7CN30WW
EC Version	A7EC30WW

STEP3: Press " \rightarrow " key to switch to [Exit] page.

STEP4: Select [OS Optimized Defaults] and set to [Win7 OS].



STEP5: Select [Load Default Settings] and select [Yes].



STEP6: Press "←" key to switch to [Configuration] page.

- STEP7: Select [USB Mode] and set to [USB 2.0].
- Note: Please download USB 3.0 driver and change back USB Mode value after Windows 7 installation

Information Configuration Secu	InsydeH20 Setup Dilling
System Time System Date USB Legacy Wireless SATA Controller Mode Power Beep Intel Virtual Technology BIOS Back Flash HotKey Mode USB Mode	E19:56:50J E01/07/2014J <enabled> <enabled> <ahci> <disabled> <disabled> <disabled> <disabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enabled> <enable< th=""></enable<></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></enabled></disabled></disabled></disabled></disabled></ahci></enabled></enabled>
	USB 2.0 USB 3.0

STEP8: Press " \rightarrow " key to switch to [Exit] page.

STEP9: Select [Exit Saving Changes] option and select [Yes] to save the changes.

Internation Contiguration	Insydeli20 Setup Utifity Security Boot Exit	
Exit Saving Changes Exit Discarding Changes Discard Changes Save Changes		BX
Load Default Settings OS Optimized Defaults	<₩in7 0\$>	
	Exit Saving Changes?	

STEP10: When Lenovo LOGO appears, press "Fn+F12" to enter "Boot Manager" menu, select the USB key / ODD to setup Windows 7.

	Boot Manager
Boot Option Henu	
Windows Boot Manager (ST320LT012-1DG14C)	
ST320LT012-1DG14C	
MATSHITA DVD-RAM UJ8FBS	
Realtek PXE 803 D00	